




Led Bar Instructions

I. Technical Parameters

1. Charger AC input: 110~220V / 50-60 Hz
2. Charger DC output: 5V, 600mA
3. Battery performance: Lithium Battery 1800mAh, charging time 5-6hrs, working for 8-12hrs.
4. Life-Span: 50,000 hours
5. Color: 16 colors, switched by remote controller, or automatically

6. Remote controller functions:

- 1). Increase brightness of a single color
 - 2). Decrease brightness of a single color
 - 3). Turn on the LED lighting
 - 4). Turn off the LED lighting
 - 5). Quick select (16 colors)
 - 6-9). Switch color modes - 4 Modes
- Remote controller using distance: 10 meter
7. charging times: 1000-1500 times



II. Material Specifications

PE Plastic- Polyethylene (LLDPE):

- (1). High hardness and strength, no water absorption, Excellent electrical insulating properties (In particular, high-frequency insulation) and radiation resistance;
- (2). Flexibility, good elongation;
- (3). Weight Bearing: 130kg

III. Battery Charging

Insert the charger into the electricity socket, then the red indicator light is on, which means the bar is charging; when the indicator light turns into green, the charging is completed.



USA/CA charger

European charger

AU/NZ charger



Warning:

When using the LED bar, reduce the risk of fire, electric shock or injury, other basic safety precautions should always be followed strictly:

1. Keep power charger away from children when in charging.
2. Do not charge when the bar is in the water.
3. Dismantling the bar is not allowed.